

Référentiel technique - Questions/Réponses

1. **Question:** J'utilise une carte mère avec codec Realtek HD Audio. Lors de la sortie de veille ou d'hibernation de Windows Vista, le périphérique audio haute définition ne fonctionne plus. Comme résoudre ce problème ?

Réponse: Ce problème est dû à Microsoft. Il peut être résolu en installant un correctif Microsoft.

Veillez vous reporter à la base de connaissances Microsoft :

<http://support.microsoft.com/kb/929685/en-us>

2. **Question:** Je dispose d'une carte mère ConRoe1333-DVI/H R2.0. Quelles sont les modules de mémoire recommandés pour cette carte mère ?

Réponse: Veuillez vous reporter à la page 17 du manuel de la carte mère.

<http://download.asrock.com/manual/ConRoe1333-DVIH%20R2.0.pdf>

Recommended Memory Configurations (DS: Double Side, SS: Single Side)

	DDRII_1 (Yellow Slot)	DDRII_2 (Orange Slot)	DDRII_3 (Yellow Slot)	DDRII_4 (Orange Slot)
1 memory module	DS/SS*	X	X	X
2 memory modules	DS/SS	X	DS/SS	X
2 memory modules	X	DS/SS	X	DS/SS
3 memory modules	SS	SS	DS/SS	X
4 memory modules	SS	SS	SS	SS

* If you only install one memory module, you can install it to any one of the four slots.

These two TRANSCEND memory modules can only be supported under the following conditions:

DRAM VENDOR	SIZE (MB)	TYPE	CELL VENDOR	CELL NO.	SINGLE SIDE / DOUBLE SIDE
TRANSCEND	256	DDRII533	SAMSUNG	K4T56083QF-ZCD5	SINGLE SIDE
TRANSCEND	512	DDRII533	INFINEON	HYB18T512800AF37	SINGLE SIDE

1. If you plan to install one above memory module, you can install it to any DDRII slot of this motherboard.
2. If you plan to install two above memory modules, it is recommended to install them either in the set of yellow slots (DDRII_1 and DDRII_3), or in the set of orange slots (DDRII_2 and DDRII_4).
3. This motherboard does not support three or four above memory modules.